



```

EXAMPLE EYETVCAMD CONFIGURATION
2 CARDS: CAID1 AND CAID2
EYETVCAMD ENTRY FOR CAID1:
----
Protocol: ncd525
User: eyetvcamd
Password: eyetvcamd
Host: 127.0.0.1
Port: 15000
Key: 0102030405060708091011121314

EYETVCAMD ENTRY FOR CAID2:
----
Protocol: ncd525
User: eyetvcamd
Password: eyetvcamd
Host: 127.0.0.1
Port: 15001
Key: 0102030405060708091011121314
  
```

```

EXAMPLE OSCAM PROXY CONFIGURATION
2 CARDS: CAID1 AND CAID2
oscam.conf
-----
# MISC
[global]
logfile=/tmp/oscam.log
nice=-1
maxlogsize=0

# WEBINTERFACE OF PROXY OSCAM
[webif]
httpport=16002
httpuser=webifoscamproxy
httppwd=webifoscamproxy
httpallowed=127.0.0.1
  
```

```

# COMMUNICATION BETWEEN EYETVCAMD AND OSCAM PROXY
[newcamd]
# MAP PORTS TO CAID:IDENT
port=15000@CAID1:000000;15001@CAID2:000000
key=0102030405060708091011121314
  
```

```

oscam.server
-----
[reader]
label=Server

# CCCAM PROTOCOL FOR OSCAM-SERVER AND CCCAM SERVER
protocol=cccam

# OSCAM/CCCAM SERVER IP AND PORT
device=192.168.178.1,12000

# SERVER USER AND PASSWORD
user=user1
password=password1

# MISC
group=1
cccversion=2.3.0
  
```

```

oscam.user
-----
# EYETVCAMD USERS
# TYPICALLY EVERY CAID:IDENT IS MAPPED TO THIS USER FROM EYETVCAMD
[account]
user = eyetvcamd
pwd = eyetvcamd
group = 1
au = 1
  
```

```

EXAMPLE OSCAM SERVER CONFIGURATION
2 CARDS: CAID1 AND CAID2
oscam.conf
-----
# MISC
[global]
logfile=/tmp/oscam.log
nice=-1
maxlogsize=0

# WEBINTERFACE OF PROXY OSCAM
[webif]
httpport=16002
httpuser=webifoscamproxy
httppwd=webifoscamproxy
httpallowed=127.0.0.1
  
```

```

# COMMUNICATION BETWEEN OSCAM PROXY AND OSCAM SERVER
[cccam]
port = 12000
version = 2.3.0
keepconnected = 1
  
```

```

oscam.server
-----
# READERS FOR CAID1 AND CAID2

[reader]
device =
caid =
ident =
detect =
mhz =
cardmhz =
...
  
```

```

oscam.user
-----
# OSCAM PROXY USERS
[account]
user = user1
pwd = password1
group = 1
au = 1
caid = CAID1, CAID2
  
```